



Communication Protocol

Date : 8 June , 2020

Version :1.0

S.No	Parameter	Parameter Type	Bytes	Address(Decimal)	Remark
1	Voltage (P-N)	int	2 Bytes	16441	
2	Current	int	2 Bytes	16442	
3	PF	int	2 Bytes	16443	
4	HZ	int	2 Bytes	16444	
5	RTC - Hour	int	2 Bytes	16445	
6	RTC - Minutes	int	2 Bytes	16446	
7	RTC - Second	int	2 Bytes	16447	
8	RTC - Date	int	2 Bytes	16448	
9	RTC - Month	int	2 Bytes	16449	
10	RTC - Year	int	2 Bytes	16450	
11	Relay On Hour	int	2 Bytes	16451	
12	Relay On Minute	int	2 Bytes	16452	
13	Relay Off Hour	int	2 Bytes	16453	
14	Relay off Minute	int	2 Bytes	16454	
15	Relay Status	int	2 Bytes	16455	
16	kW	int	4 Bytes	16456	
17	EB-Energy	int	4 Bytes	16458	
19	Location ID	int	4 Bytes	16460	
20	Astronomical Disable/Enable	int	2 Bytes	16477	
21	12 Month On Hour and Minutes	int	2 Bytes	16478	
22	13 Month OFF Hour and Minutes	int	2 Bytes	16490	
23	Mode (0=Normal,1=Manual,	int	2 Bytes	16502	
24	Test Mode Time	int	2 Bytes	16503	

Verified By : Vinod

Checked By : N.C

Created By : A.J

Enertrak Instruments Private Limited, Jaipur

www.enertrak.in

Note

- 1 This is a computer generated document and does not require any signature.
- 2 Due to continuous improvement of product the technical parameters might change from time to time.